



## PRODUCT FEATURES:

- Easy retro fit installation
- Low battery cut-out to protect battery from over discharge
- Fast charging of various battery chemistries
- Mains Fail, Fuse Fail and Low Battery reporting to the IDS XSeries Smart Zone Expander (860-06-700)

Supply Voltage		20-24VDC 1.5A
Charging Voltage		14VDC
Maximum charging current		1A
Low battery cut out		10V-10.5V
Dimensions	Length	122mm
	Width	26mm
	Height	20mm
Operating temperature		0-55 °C
Supported battery chemistries		Gel, Lead-Acid, Lithium

**Africa's leading manufacturer and distributor of electronic security products.**